


The Or Register instruction performs a logical bit by bit “or” between two registers. Operand 1, the target, is a register and Operand 2, the source, also specifies a register. The fullword in Operand 1 is or-ed internally with the fullword in Operand 2, and the result is placed in Operand 1. The table below shows the results of “or-ing” two bits together.

Bit 1	Bit 2	Result
0	0	0
0	1	1
1	0	1
1	1	1

This instruction sets the condition code as follows:

- 0 if all target bits are set to 0. Test this condition with **BZ** or **BNZ**.
- 1 if any target bit is set to 1. Test this condition with **BM** or **BNM**.



Some Unrelated Or Registers

```

R4 = X'FFFFFFFF'    ALL 1'S
R5 = X'00000000'    ALL 0'S
R6 = X'0000148C'    000000000000000000001010010001100
R7 = X'000014AB'    0000000000000000000001010010101011
R8 = X'1A3359CF'    00011010001100110101100111001111
R9 = X'8CF4594A'    10001100111101000101100101001010

```

```

OR   R4,R4    R4 = X'FFFFFFFF' Condition Code = 1
OR   R4,R5    R4 = X'FFFFFFFF' Condition Code = 1
OR   R4,R6    R4 = X'FFFFFFFF' Condition Code = 1
OR   R4,R7    R4 = X'FFFFFFFF' Condition Code = 1
OR   R5,R5    R5 = X'00000000' Condition Code = 0
OR   R5,R6    R5 = X'0000148C' Condition Code = 1
OR   R5,R7    R5 = X'000014AB' Condition Code = 1
OR   R6,R7    R6 = X'000014AF' Condition Code = 1
OR   R7,R7    R7 = X'000014AB' Condition Code = 1
OR   R8,R9    R8 = X'9EF759CF' Condition Code = 1

```